

Contents in this document may change without prior notice.
Please obtain the delivery specification for the final design.



7.0" Wide (WVGA)

Resistive Touchscreen Module with LCD

Simple Set Plus

TK-S Series

Model: TK-SRA07BWV-01A4

Product Specification

DMC Co., Ltd.

<https://www.dush.co.jp/english/>

Table of Contents

1	Summary	3
2	Product Model	3
3	Components	3
4	Packaging Specification	4
4-1	Grouped packaging	4
4-2	Individual Packaging	6
5	Module Specification	7
5-1	Function	7
5-2	General Specification	7
5-3	Environment	8
5-4	Mechanical Specification	8
5-5	Touchscreen Controller	8
5-6	Touchscreen Driver	8
5-7	HDMI Board Specification	9
5-7-1	Model	9
5-7-2	External Dimension	9
5-7-3	Support Timing	10
5-7-4	Part Names (HDMI Board)	10
5-7-5	Image Input (HDMI) I/F	11
5-7-6	12VDC Power Input I/F	11
5-7-7	LCD Backlight Control I/F	12
5-7-8	LCD (LVDS) Output I/F	12
6	Product Label	13
7	Compliant Standards	13
7-1	RoHS	13
8	Appearance inspection standard	13
9	Option Items	14
10	Connecting Method	14
10-1	Connecting Diagram	14
10-2	Connecting Image Cable to LCD	14
10-3	Connecting Touchscreen tail to Touchscreen Controller	15
10-4	Connecting Image Cable to HDMI Board	15
10-5	Connecting USB Cable to Touchscreen Controller	16
10-6	Connecting Each Cable to User I/F of HDMI Board	16
11	Touchscreen Calibration	17
11-1	Resistive Touchscreen	17
12	Terms of Use	19
12-1	Installing Module	19
12-2	Precautions for Use of LCD	19
12-3	Precautions for Resistive Touchscreen	19
12-4	Precautions for Static Electricity	20
12-5	Operating Precautions	20
12-6	Storing Precautions	20

12-7	Handling Precautions	20
13	Warranty	21
14	Production Discontinuance	21
15	Other	22

Appendix

- Outline Drawing (SM3-002528-10)
- Appearance inspection standard
(LCD Modules with Resistive Touchscreen)(22G4GX-00001E)

Downloads : <https://www.dush.co.jp/english/download/>

- Resistive Touch Screen Mounting Guidance (LST-series)
- Touch Screen Controller Specification: TSC-54/RU User's Guide

1 Summary

This is a “TK series Simple Set Plus” with 7.0" Wide resistive touchscreen sensor, controller, and LCD (Liquid Crystal Display) plus HDMI Board.

2 Product Model

Model	Specification			
	LCD size (Resolution)	Touchscreen Type	Bonding Method	Set Type
TK-SRA07BWV-01A4	7.0" Wide (WVGA)	Resistive	Air-bonding *	Simple Set Plus

* Bonding of LCD and touchscreen with double-sided tape.

3 Components

Components	Name	Specification	Manufacturer	Model
TS+LCD	Touchscreen (TS)	Resistive	DMC	LST-070WB080A
	LCD	7.0" Wide	INNOLUX	G070ACE-L01
Accessories	Touchscreen controller	-	DMC	TSC-54/RU
	HDMI board	HDMI input	DMC	SWAD-A4
	Image cable (L: 200mm)	-	DMC	24E3E4-00012

4 Packaging Specification


Depending on the number of shipments, individual packaging may be used instead of grouped packaging.

4-1 Grouped packaging

Box	Contents	Specification	Size (W x D x H)
A	TS+LCD	Grouped packaging (10units/box)*	External dimension: 457×295×151
B	Accessories	Grouped packaging (10pcs/box)*	External dimension: 457×295×151


※May not be as specified according to the quantity shipped.

• Grouped Packaging Configuration (A)



No.	Name		Qty
①	TS+LCD (placed inside antistatic bag, placed inside air-cushion bag) * Touchscreen with protective sheet		10
②	Outer box		1
③	Top/Bottom pad		2
④	Partition Set	Partition A	3
		Partition B	6
⑤	Grouped packaging label		1

• Grouped Packaging Configuration (B)



No.	Name		Qty
①	HDMI board (placed inside antistatic bag, placed inside air-cushion bag)		10
	Touchscreen controller (placed inside antistatic bag, placed inside air-cushion bag)		
	Image cable (placed inside antistatic bag, placed inside air-cushion bag)		
②	Outer box		1
③	Top/Bottom pad		2
④	Partition Set	Partition A	3
		Partition B	6
⑤	Grouped packaging label		1


4-2 Individual Packaging

Box	Contents	Specification	Size (W x D x H)
C	TS+LCD, Accessories	Individual packaging (1unit/box)	External Dimension: 287 x 176 x 55

※One box includes TS+LCD and accessories.

• Individual Packaging Configuration(C)

No.	Name	Qty
①	TS+LCD (placed inside antistatic bag, placed inside air-cushion bag) * Touchscreen with protective sheet	1
	HDMI board (placed inside antistatic bag, placed inside air-cushion bag)	
	Touchscreen controller (placed inside antistatic bag, placed inside air-cushion bag)	
	Image cable (placed inside antistatic bag, placed inside air-cushion bag)	
②	Outer box	1
③	Packaging label	1



5 Module Specification

5-1 Function

Item			Specification	units
LCD	Display device		7.0" Wide TFT LCD	-
	Display area (Active area)		152.4(W) ×91.44(H)	mm
	Pixels		800(W) ×480(H)	-
	Pixel pitch		0.1905(W) ×0.1905(H)	mm
	Color		16.7M	colors
	Brightness (Typ.)		395	cd/m ²
	View angle (Typ.)	Vertical (Upper/Lower)	89 / 89	deg.
		Horizontal (Left/Right)	89 / 89	
	Interface		LVDS	-
	Backlight method		LED, with backlight driver	-
	Backlight life*1		Min. 50,000	hours
Touchscreen	Touchscreen type		Analog 4-wire resistive	-
	Input method		Finger or R0.8 Polyacetal pen	-
	Maximum simultaneous input point		1 point	-
	Operating life	Continuous input (finger)	10 million times	
		Continuous input (pen)	100,000	characters
	Communication Method		USB 2.0	-
	Supporting OS		*2	-
HDMI board	The tail Bending Resistivity		1mm≤R *3	-
	Input image port		HDMI (does not support HDCP)	-
	Input Signal	Digital	HDMI 1.3b	-
		Horizontal scan cycle	30K - 80K	Hz
		Vertical scan cycle	50 - 75	Hz

*1. Time until the backlight brightness declines by 50% from the initial value when continuously turned on at maximum brightness at the ambient temperature of 25°C.

*2. Please refer to the "Touchscreen Controller OS Compatibility Table".

(<https://www.dush.co.jp/english/download/driver-app/>) (Touchscreen controller referenced: TSC-54/55)

*3. Do not bend if R<1mm as it may break.

5-2 General Specification

Item		Specification
Power	Input power voltage	12VDC±5%
	Power consumption	Max. 4.0W

Note: If the capacity of the power supply used is large, the drop in voltage when it is turned off will be gradual. When restarting, please turn on the power again after the power supply voltage becomes 0V.

5-3 Environment

Item	Specification
Ambient operating temperature (Inside cabinet and display side)	0°C to 55°C
Ambient storage temperature	-20°C to 70°C
Ambient operating humidity	10%RH to 85%RH (Non-condensing. Wet-bulb temperature is 39 °C or less)
Ambient storage humidity	10%RH to 85%RH (Non-condensing. Wet-bulb temperature is 39 °C or less)
Dust	0.1mg/m ³ or under (Conductive dust is prohibited)
Corrosive Gas	Corrosive gas is prohibited
Pollution Degree	Pollution Degree 2, for indoor use

5-4 Mechanical Specification

Item	Specification	
Mass	TS (Touchscreen) + LCD	Approx. 240 g
	Touchscreen controller	Approx. 8 g
	HDMI board	Approx. 30 g
External Measurements (TS (Touchscreen)) + LCD, excluding protruding parts)	170.75(W)×110(H)×10.5(D) mm	

5-5 Touchscreen Controller

For details, please refer to the downloadable document "Touch Screen Controller Specification: TSC-54/RU User's Guide" in the table of contents.

5-6 Touchscreen Driver

To obtain the touchscreen driver (DMT-DD), please download it from the following site.

URL: <https://www.dush.co.jp/english/download/driver-app/>

For DMT-DD installing directions, please refer to the User's Guide included in the downloaded files.


5-7 HDMI Board Specification

5-7-1 Model

Model	Image Input Port
SWAD-A4	HDMI ×1

5-7-2 External Dimension


Item	Measurement
PCB outline (excluding connector)	65mm x 65 mm



5-7-3 Support Timing

No	Resolution	Refresh Rate
1	640×480p	60/75Hz
2	800×480p	60/75Hz

5-7-4 Part Names (HDMI Board)



No.	Interface Name
①	Image input (HDMI)
②	12VDC Power input (Nylon connector)
③	LCD Backlight control
④	LCD Image output (LVDS)


Note: Use of other connectors not listed is prohibited. These are only internal adjustments for the manufacturer and may be excluded without prior notice.

5-7-5 Image Input (HDMI) I/F

Connector No.: HDMI Board CN8

Interface: HDMI Type A

Note: HDMI standard compliant

PIN No	Signal Name	PIN No	Signal Name	Schematic Diagram
1	TMDS Data2+	11	TMDS Clock Shield	
2	TMDS Data2 Shield*	12	TMDS Clock-	
3	TMDS Data2-	13	CEC (NC)	
4	TMDS Data1+	14	Reserved	
5	TMDS Data1 Shield	15	DDC Clock	
6	TMDS Data1-	16	DDC Data	
7	TMDS Data0+	17	DDC GND	
8	TMDS Data0 Shield	18	+5V Power	
9	TMDS Data0-	19	Hot Plug Detect	
10	TMDS Clock+	-	-	

* Pin 2 has the function of TMDS Data 2 Shield and the role of detecting a PC connection. Please make sure that PCs whose HDMI Pin 2 has the role of detecting a monitor connection as well as this product cannot be connected.


5-7-6 12VDC Power Input I/F

Connector No.: HDMI Board CN1

Interface: +12VDC Input

Connector: MK242151P3(ZONE TECH TECHNOLOGY)

Note: Equivalent to B03B-PASK-1 (JST)

PIN No.	Signal Name	Schematic Diagram
1	+12V	
2	GND	
3	GND	

5-7-7 LCD Backlight Control I/F

Connector No.: CN7

Connector: C1U20-060V-R (TACT PRECISION INDUSTRIAL)

Note: Equivalent to B6B-PH-K-S(LF)(SN) (JST)

PIN No.	Signal Name	Description
1	12V	Backlight power
2	12V	
3	GND	Ground
4	BL_PWM	Backlight dimming input
5	GND	Ground
6	BL_EN	Backlight ON/OFF High level : Backlight ON. Low level : Backlight OFF.

5-7-8 LCD(LVDS) Output I/F

Connector No.: CN4

Interface: LVDS

Connector: CI0130P1VDL-01-NH (CviLux)

PIN No.	Signal Name	PIN No.	Signal Name
1	Panel VCC 3.3V	16	GND
2	Panel VCC 3.3V	17	RXE0-
3	RXO0-	18	RXE0+
4	RXO0+	19	RXE1-
5	RXO1-	20	RXE1+
6	RXO1+	21	RXE2-
7	RXO2-	22	RXE2+
8	RXO2+	23	GND
9	GND	24	GND
10	GND -	25	RXEC-
11	RXOC-	26	RXEC+
12	RXOC+	27	RXE3-
13	RXO3-	28	RXE3+
14	RXO3+	29	NC
15	GND	30	NC


6 Product Label



Above is an image example of the product label.

The below information will be indicated on the actual product.

- Model: Product Model
- Serial No.: 10 digit control number
- Revision: Alphabets (A to Z) according to the product revision



7 Compliant Standards

7-1 RoHS

Compliant to EU RoHS directives.

8 Appearance inspection standard

Please refer to "Appearance inspection standard (LCD Modules with Resistive Touchscreen)" (22G4GX-00001E) for standards.


9 Option Items

■Controller Cable

Model	Specification
TSC-10/SC	USB cable for connecting host (USB-TypeA) and touchscreen controller (L:1800mm).



10 Connecting Method

10-1 Connecting Diagram




10-2 Connecting Image Cable to LCD

- (1) Slide the housing of the image cable into the connector on the backside of the LCD in the direction shown below.




10-3 Connecting Touchscreen tail to Touchscreen Controller

- (1) Insert securely into the FPC connector of the touchscreen controller in the direction with the touchscreen tail visible.




10-4 Connecting Image Cable to HDMI Board

- (1) Insert the image cables securely into the connector of the HDMI board while mating the Bump and Dip of each connector to prevent incorrect insertion, as shown in the pictures below.




- (2) Insert the backlight cable securely into the connector of the HDMI board, as shown in the pictures below.



10-5 Connecting USB Cable to Touchscreen Controller


- (1) Insert the USB cable securely into the connector of the touchscreen controller as shown in the pictures below.



- * USB cable not included.
- * USB cable in the photos is the option item

10-6 Connecting Each Cable to User I/F of HDMI Board

- (1) Connecting the HDMI cable and the Power cable



- ※Please insert securely.
- ※HDMI cable/ Power cable not included.

11 Touchscreen Calibration

Touchscreen operations may become unstable depending on the installation environment due to its characteristics. To use it correctly, please perform calibration when building into a device.


Install DMT-DD from “[5-6. Touchscreen Driver](#)” when calibrating.

11-1 Resistive Touchscreen

[4 Point] or [9 Point] calibration ▪ ▪ ▪ Coordinate calibration.

(1) Start [DMT-DD].

(2) Choose the [Software Setting] via [Basic Setting]



(3) Put the check mark [Use EEPROM] under [EEPROM] and click [Entry].

When [4 Point] or [9 Point] calibration is performed with the check mark, the correction data will be stored in the EEPROM of the touchscreen controller.

When [4 Point] or [9 Point] calibration is performed without the check mark, the correction data will be stored inside the computer.


[4 Point] calibration is performed on this product at the factory shipment and the correction data is already stored in the EEPROM.

Putting the check mark [Use EEPROM] recalls the stored correction data from the EEPROM, but the touch coordinates may be misaligned depending on the combination of touchscreen and touchscreen controller.


Please perform the coordinate calibration according to the following procedure in case touch coordinates are out of alignment.

When using this product without the check mark [Use EEPROM], the stored correction data at the factory shipment will not be reflected, and accurate touch operations may not be possible.

- (4) The below calibration image will be displayed when [4 Point] or [9 Point] calibration is clicked.



- (5) Touch the center of the marker displayed on the screen. Another marker will be displayed one after another. Do the same for all.
- (6) After all markers have been touched, adjustment is completed, and the following screen will be displayed.



- (7) Click [OK] to finish the adjustment.

12 Terms of Use

12-1 Installing Module

- (1) For stable brightness and display, connect the GND via the mounting hole on the LCD.
- (2) Install the module so that no external pressure is applied to the LSI mounting area.
- (3) Make sure there are no warping and twisting when installing.
- (4) Make sure the specified temperature and humidity between the module and other structures or parts are taken into consideration to secure ventilation.
- (5) Take anti-static measures such as wearing earthing bands for grounding during assembly.
- (6) To prevent malfunction or damage, make sure the connectors of the connecting cables are inserted securely.
- (7) Remove the protection sheet on the touchscreen when installing.
- (8) Be sure to fix the LCD when mounting the module to a chassis. Since the LCD and the touchscreen are attached with double-sided tape, the LCD may fall off if only the touchscreen side is fixed.

12-2 Precautions for Use of LCD

- (1) The LCD contains irritants inside. If by any chance the liquid should flow out due to damage and come in contact with the skin, wash immediately under running water for more than 15 minutes and consult a physician.
- (2) LCD may have uneven brightness depending on the contents displayed. Please note that this is not a malfunction.
- (3) LCD elements may have spots (black spots/ bright spots). This is a characteristic of the LCD and not a malfunction.
- (4) When the screen is viewed outside the viewing angle, the color displayed may appear to change. This is a basic characteristic of the LCD and not a malfunction.
- (5) When the same image is displayed for a certain long period of time, the image may remain as an afterimage. This is a basic characteristic of the LCD.
In order to avoid afterimages, use a screensaver or other similar functions to periodically change the displayed image and avoid displaying the same image for a long period of time.

12-3 Precautions for Resistive Touchscreen

- (1) Applications that require to press the same point on the touchscreen for a long time may cause malfunction due to the structure of the touchscreen.
The touchscreen is made of glass. Glass is easily damaged when scratched.
Please handle the touchscreen so that glass does not come in contact with other glass or hard objects.
- (2) The touchscreen is made of glass. Glass can easily break if scratched.
Please handle the touchscreen so that glass does not hit other glass or hard objects.
- (3) Due to the characteristics of the touchscreen, the area slightly outside the display area may be detected as the coordinates of the edge of the touchscreen. Please design your application with this in mind.
- (4) The coordinates of the touchscreen may shift over time or depending on the environment in which it is used. If the touchscreen coordinates get misaligned, please perform the coordinate calibration.
- (5) Handle the edge of the glass with care as it may cause injuries.

12-4 Precautions for Static Electricity

- (1) Static Electricity may cause damage. Please take sufficient measurements when handling.
- (2) Operators should take anti-static measures such as wearing earthing bands for grounding.

12-5 Operating Precautions

- (1) When used outside the specification standards, it may significantly affect the product quality and service life, such as degradation of display quality and generation of air bubbles. Please be sure to use it within the standards.

12-6 Storing Precautions

- (1) When storing the module, please avoid areas of high temperature and humidity. Especially when storing for a long period of time, make sure to store it in a place that is not exposed to direct sunlight and/or fluorescent lighting.
- (2) Please store the module in a condition where it is not subject to excessive load.

12-7 Handling Precautions

- (1) Do not leave the product in an environment with high temperature for a prolonged period. Make sure to avoid high humidity especially when the temperature is above 40°C. Failing to do so may cause polarizing plate deterioration, peeling, and/or bubbles to form.
- (2) If the surface of the polarizing plate becomes dirty, wipe it lightly with a soft material such as cotton cloth moistened with a small amount of ethyl alcohol.
- (3) Condensation on the polarizing plate during testing is prohibited to prevent staining, discoloration, or forming spots on the plate.
- (4) Disassembling the module and/or changing the volume of the module are prohibited. Doing so may cause malfunction and failure to perform correctly.
- (5) This product is intended for use in general electronic equipment and is not intended for use in special environments such as a corrosive gas atmosphere. If use in a special environment is anticipated, please evaluate thoroughly or take precautions not to expose the LCD to corrosive gases, etc.
- (6) This product is intended for use in standard applications (office equipment, industrial, communication, household equipment, etc.). Do not use the products for special applications that require extremely high reliability (e.g., aerospace, nuclear power control, medical applications for life support, etc.) or where malfunctions or failures may directly cause injuries to the human body.
- (7) Do not rub or press the product with hard or sharp objects.
- (8) Keep away from flames/fire.
- (9) Avoid wiping the product with excessive pressure.
- (10) Avoid locally rubbing the product with strong pressure. It may cause damage to the function of the touchscreen.
- (11) When operating the product, please avoid striking it with a hard object.
- (12) Do not forcibly fold or bend the product.
- (13) When storing the product, use the packing box and keep the product within the specified storage temperature and humidity and in an environment where it is free of excessive pressure and loads.
- (14) Avoid using and storing the product where it can be exposed to or come in contact with

liquids, organic solvents, and an acidic atmosphere.

- (15) Avoid using the product in direct sunlight.
- (16) Do not pull off or disassemble the product.
- (17) When handling the product, hold the main unit and not the touchscreen FPC (tail).
- (18) EMC (EMS, EMI) evaluation is not conducted at shipment. Please conduct an overall evaluation and confirmation after the product has been installed in your equipment.

13 Warranty

The warranty period is limited to 12 months (1 year) from the date of shipment. Any defects that occur upon normal use under conditions specified herein will be repaired (factory repair) free of charge. (Warranty for any repair needed to the same repaired part of the same product is three months.)

You will be liable for all repair fees even within the warranty period for any conditions listed below.

- (1) Any malfunctions, defects, and/or damages that occurred during transport, transfer, or mishandling by the user after delivery.
- (2) Any malfunctions, defects, and/or damages caused by natural or man-made disaster.
- (3) If the product is used under any condition, environment, or method other than those specified in the specifications, catalogs, manuals, notes, and/or other documents.
- (4) Any malfunctions, defects, and/or damages caused by connected equipment and/or usage of inappropriate consumables and media.
- (5) If the product is repaired, remodeled, modified, or disassembled by a party other than DMC Co., Ltd, or if a serial number label cannot be verified.
- (6) Any failure, damage, or malfunction is deemed to be caused on your behalf.

This warranty covers only the product itself. No warranty is provided for damage, on-site repair, or replacement resulting from product failure.

14 Production Discontinuance

In the event of production discontinuance, an announcement will be made six months prior to the last possible order reception date.

15 Other

For comments or queries, feel free to contact us.

North South America area

technical-global@dush.co.jp

Asia Pacific area

technical-global-asia@dush.co.jp

Europe, Middle East, Africa area

technical-global-eu@dush.co.jp

FAQ

<https://www.dush.co.jp/english/support/faq/>

1st Edition, April 2025

DMC Co., Ltd.


Business hours: 9:00a.m.~5:00p.m. (JST)

URL: <https://www.dush.co.jp/english/>


This document is protected by copyright law. Photocopying, duplicating, reproducing, and modifying of this product or document in part or by whole is prohibited.

Copyright(C) 2025 DMC Co., Ltd. All Rights Reserved

SYM	改訂日	改訂内容	ページ	担当
	DATE		PAGE	DESIGNED
	2025. 01. 29	新規図面登録	—	S. Takada



- NOTES
- タッチ方式：抵抗膜方式
Type: Resistive Touchscreen
 - ITOガラス：厚さ1.1mm
ITO Glass: thickness 1.1mm
 - LCD Connector：093G30-B0001A (STARCONN)
 - 指示無き寸法公差は、±0.5mmとする。
Tolerance shall be of ±0.5mm Unless specified otherwise.

製図日 ISSUED	2025, 01, 29	部署 SECTION	Technical Dept.	尺度 SCALE	CAD登録名 CAD FILE NAME	OUTLINE_TK-SRA07BWV-01		RoHS対応品 RoHS compliant	
承認 APPROVED	検図 CHECKED	製図 DRAWN	設計 DESIGNED	1:2	製品名 MODEL	TK-SRA07BWV-01			
T. Okada	S. Yoshimoto	S. Takada	S. Takada	単位 UNIT		図名 TITLE	OUTLINE	ページ PAGE	1 / 1
				mm					
DMC Co., Ltd.			A3		図番 DWG No.	SM3-002528-10			

Appearance Inspection Standard (1)


1.1 Inspection condition

Inspection Distance : 35 ± 5 cm

View Angle : Inspection under non-operating condition : $\pm 30^\circ$

Ambient Illumination : 500~2000 lux

Inspection time : 3~5 seconds



1.2 Scratch, dust (W = width, L = length, D = average diameter = (longest + shortest) / 2))

Total defects on each panel.

【 14 inches < Size ≤ 22 inches 】	Within 10 pcs / panel
【 10 inches < Size ≤ 14 inches 】	Within 7 pcs / panel
【 Size ≤ 10 inches 】	Within 5 pcs / panel

Item	Width(mm)	Length(mm)	Acceptable Numbers
Linear(Scratch/Dust) Over 0.1mm in diameter refer to the Circular.	$0.05 < W \leq 0.1$	$L \leq 4$	1pcs in $\phi 30\text{mm}$
	$0.03 < W \leq 0.05$	$L \leq 10$	2pcs in $\phi 20\text{mm}$
	$W \leq 0.03$	$L \leq 20$	Acceptable
Circular(Scratch/Dust)	$0.3 < D \leq 0.4$		1pcs in viewing area *1
	$0.2 < D \leq 0.3$		2pcs in $\phi 30\text{mm}$
	$D \leq 0.2$		Acceptable

Applied only in the Viewing Area.

Scratches or dusts in the outside of the Viewing Area are acceptable unless the electrical characteristics are affected.




*1 Applied to 14 inches or larger panel.

• Acceptable if not noticeable on a black mat.

Product	LCD Modules with Resistive Touchscreen	Document No.	22G4GX-00001E-0
---------	--	--------------	-----------------

Appearance Inspection Standard (2)

1.3 Chip, crack (t = glass thickness) (applicable only for the glass)

Item	Size(mm)			Acceptable Numbers
Corner		X	≤ 3	2pcs /panel
		Y	≤ 3	
		Z	$\leq t$	
Side		X	≤ 5	2 pcs /on one side
		Y	≤ 3	
		Z	$\leq t$	
Crack				Not acceptable